

HS Amphe-Lite Series Industrial High Speed Amphe-Lite



Commercial D38999 High Speed Diversity Speeding Industrial Revolution

Company Profile

Established in 2007, Amphenol Technology (Zhuhai) Co., Ltd. is a manufacturing facility for Amphenol Industrial Operations, which serves a number of industrial markets, included but not limited to Factory Automation, Transportation, Heavy Equipment, Alternative Energy, Oil & Gas, Server/Data Comm and Power Distribution.

Amphenol Technology (Zhuhai) Co., Ltd. covers an area of 306,449 square feet (28,470m²) and is equipped with CNCs, plating, injection molding and assembly workshops. This plant specializes in the design and manufacturing of industrial connectors featuring high power, high density inserts, medium to high voltage electrical properties, and harsh environment applications. Many of the products produced here have been certified by independent standards including UL, IEC/TUV, ATEX, IECEx and MA. The facility is also certified to ISO 9001, ISO 14001 and TS16949.



Table of Contents

•	Markets and ApplicationsP	'3
•	Features & BenefitsP	4
•	Differential Quadrax ContactsF	> 5
•	Quadrax SpecificationsP	6
•	Split Pair Quadrax ContactsP	7י
•	Insert Arrangement OverviewF	> 8
•	Insert Arrangement LayoutsP	' 9
•	Ordering Guide and DimensionsP1	10
•	Amphe-Lite Shell Ordering GuideP1	11

Markets and Applications



RMT



Intelligent Equipment



Heavy-duty Off-Road Vehicles



Industrial Datalink

Datalink Solutions for the Industrial Environment

- MWB-WTB Signal
- High-Speed Ethernet
- Cockpit (Display + Communications)
- Datalink in vibration and harsh environment

Protocols

- 10/100/1000/10GBASE-T Ethernet
- DVI
- USB 2.0, 3.0
- Serial Rapid IO (up to 3.125Gbps)
- PCI-Express 2.0
- HDMI1.3a

Funct	Function Performance		Adoptabililty	Handling
 Anti-vibra shock Scoop pr robust de EMI shie 	esign	 High bandwidth for high speed protocol Meet MIL-D38999 criterion 	 High density (up to 99 contacts) Hybrid signal and power Drop in design for #8 cavity Crimp and PC tail versions available 	 Rear release contacts Front and rear mount

Description

High data transfer rates, low power consumption, excellent EMI compatibility.

Main Features

- Two 100 Ohm matched impedance differential pairs.
- The outer contact has a rugged wall section for durability.
- Available in size 8 crimp termination or PC tails.
- Requires modification of MIL-DTL-38999 connector to accommodate keyed contacts.

Size 8 Quadrax Performance

- Bandwidth: Up to 1.25GHz
- Data Rate: Exceeding 2.5Gbps
- Voltage Rating: 500 Vrms max.@sea level
- Dielectric Withstanding Voltage: 1000 VAC rms between all inner contacts @sea level, 500 VAC rms between inner and outer contacts @sea level



Quadrax Specifications

Mechanical

- Durability: Minimum 500 cycles
- Shock: EN2591-402 method A
- Vibration (MIL-DTL-38999) : EN2591-40
- Method A : Sinusoidal
- Method B (figure 3 and table 2, level J) : Random

Environmental

- Salt Spray: 48 hours minimum
- Temperature Range: -55°C to +125°C

Material

- Inner Contact: Copper Alloy
- Body: Copper Alloy
- Insulator: Thermoplastic
- Contact Plating: Gold Over Nickel Plated
- Contact Resistance Signal Contacts (Low Level): Initial 6mΩ, after testing 7,5mΩ
- Consult Amphenol Industrial Operations for resistance changes under current and temperature
- For Signal Integrity, consult Amphenol Industrial Operations





Description

For use with CAT 5E or CAT 6A type cable.

Main Features

- Two 100 Ohm matched impedance differential pairs.
- The outer contact has a rugged wall section for durability.
- Available in size 8 crimp termination or PC tails.
- Requires modification of MIL-DTL-38999 connector to accommodate keyed contacts.

Size 8 Split Pair Quadrax Performance

- Supports up to 6.5 Gbps per pair
- Enhanced crosstalk performance (compared to standard quadrax)
- Can be used for a variety of high speed applications beyond current quadrax design

Applications

- 10/100/1000/10GBASE-T Ethernet DVI USB 2.0, 3.0
 HDMI 1.3a •
- Serial Rapid IO (up to 3.125 Gbps) PCI-Express 2.0 SATA 2.0 (up to 3 GHz)





SOCKET CONTACT MATING FACE



Insert Arrangement Overview

Insert Pattern	Service Rating	Total Contacts	22D	20	16	12	12 SZ Coax	8 SZ Quadrax
17-2•	М	39	38					1
17-22★	Coax	4					2	2
19-31	М	15	12			1		2
21-75★●	М	4						4
23-6★	М	6						6
25-7●	NA	99	97					2
25-8★	NA	8						8
25-17	М	42	36					6
25-20	Ν	31		10	13		4	3
25-26	I	25		16		5		4
25-46●	I	46		40	4			2

★ Indicates ground plane option avaliable

• Indicates split pair Quadrax avaliable

Insert Arrangement Layouts

Notice: 1. Any size 8 can be replaced by Twinax or Quadrax.										$\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} $	
Insert Arrangment	17	7-2	17-22			19-31		21-75	23-6	25	5-7
Service Rating	1	М	Coax		М			М	М	N	A
Number of Contacts	38	1	2	2	2	1	12	4	6	97	2
Contact Size	22D	8	12 Coax	8	8	12	22D	8	8	22D	8

Notice: 1. Any size 8 can be replaced by Twinax or Quadrax.	I. Any size 8 can be eplaced by Twinax		$\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \begin{array}{c} \end{array}{} \\ \end{array}{} \end{array}{} \end{array}{} \\ \end{array}{} \end{array}{} \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \end{array}{} \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \\ \end{array}{} \\ \end{array}{} \end{array}{} \\ \end{array}{} \\$ {} \\ \\ \\ \\ \\ } \\ \\ \\ \\ \\\\ \end{array}{} \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\		$\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} $						$\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \begin{array}{c} \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} $				
Insert Arrangment	25-8	25	25-17		25	5-20			25-26			25-46			
Service Rating	NA	М		М				N			I			М	
Number of Contacts	8	36	6	10	13	3	4	16	5	4	40	4	2		
Contact Size	8	22D	8	20	16	8	12 Coax	20	12	8	20	16	8		

Service Rating

Service		l Operating Sea Level)	Test Voltage		
Rating	AC(RMS)	DC	(Sea Level)		
М	400	550	1300 VRMS		
N	300	450	1000 VRMS		
I	600	850	1800 VRMS		
II	900	1250	2300 VRMS		

Contact	Crimp Well Data						
Size	Well Diameter	Norminal Well Depth					
22D	.0345±.0010	.141					
20	.047±.001	.209					
16	.067±.001	.209					
12	.100±.002	.209					
10 (Power)	.137±.002	.355					

Contact Rating

Contact Size	Test C	urrent	Maximum Millivolt Drop
Contact Size	Crimp	Hermetic	Crimp*
22D	5	3	73
20	7.5	5	55
16	13	10	49
12	23	17	42
10 (Power)	33	NA	33

Quadrax Contacts Ordering Guide

Impedance (Ohms)	Inner Conductor (AWG)	Electrical Protocol†† Cable	PN	Pin or Socket	Cable OD	Termination Instruction Sheet
	24	1000 Base-T Gigabit Ethernet	ALQC-AA8-PB	Pin	.170~.206 inch	
1000			ALQC-AA8-SB	Socket	.170~.206 inch	
100Ω			ALQC-AA8-PA	Pin	.124~.165 inch	L-2119-D
			ALQC-AA8-SA	Socket	.124~.165 inch	

Quadrax Contacts Dimensions



Split Pair Quadrax Socket

22.56

Split Pair Quadrax Pin

22.56

7.62



Amphenol



Amphenol Industrial Operations Phone: 888-364-9011 20 Valley Street Endwell, NY13760-3600 www.amphenol-industrial.com Amphenol Technology (Zhuhai) Co., Ltd. No.63, Xinghan Road, Sanzao Town, Jinwan, Zhuhai, 519040 China www.amphenol-industrial.com

Notice: Specifications arsubject to change without notice. Contact your nearest Amphenol Corporation Sales Office for the latest specifications. All statements, information and data given herein are believed to be accurate and reliable but are presented without guarantee, warranty, or responsibility of any kind expressed or implied. Statements or suggestions concerning possible use of our products are made without representation or warranty that any such use is free of patent infringement and are not recommendations to infringe any patent. The user should not assume that all safety measures are indicated or that other measures may not be required. Specifications are typical and may not apply to all connectors.