Features

- Low-voltage and Standard-voltage Operation
 - $-2.7 (V_{CC} = 2.7V \text{ to } 5.5V)$
 - -1.8 (V_{CC} = 1.8V to 3.6V)
- Internally Organized 16,384 x 8 and 32,768 x 8
- 2-wire Serial Interface
- Schmitt Trigger, Filtered Inputs for Noise Suppression
- Bidirectional Data Transfer Protocol
- 1 MHz (5V), 400 kHz (2.7V, 2.5V) and 100 kHz (1.8V) Compatibility
- Write Protect Pin for Hardware and Software Data Protection
- 64-byte Page Write Mode (Partial Page Writes Allowed)
- Self-timed Write Cycle (5 ms Max)
- High Reliability
 - Endurance: One Million Write Cycles
 - Data Retention: 40 Years
- Extended Temperature and Lead-free/Halogen-free
- **Devices Available** • 8-lead JEDEC PDIP, 8-lead JEDEC and EIAJ SOIC, 8-lead MAP, 8-lead TSSOP and 8-ball dBGA2[™] Packages

Description

The AT24C128/256 provides 131,072/262,144 bits of serial electrically erasable and programmable read only memory (EEPROM) organized as 16,384/32,768 words of 8 bits each. The device's cascadable feature allows up to 4 devices to share a common 2-wire bus. The device is optimized for use in many industrial and commercial applications where low power and low voltage operation are essential. The devices are available in space-saving 8-lead JEDEC PDIP, 8-lead JEDEC SOIC, 8-lead EIAJ SOIC, 8-lead MAP (24C128), 8-lead TSSOP and 8-ball dBGA2 packages. In addition, the entire family is available in 2.7V (2.7V to 5.5V) and 1.8V (1.8V to 3.6V) versions.

A0 🗆

A1 🗆 2 NC 🗆

GND 🗆 4

VCC

WP (7) 2 A1

SCL 6 3 NC 4

SDA 5

3



2-wire Serial **EEPROMs**

128K (16,384 x 8)

256K (32,768 x 8)

AT24C128 AT24C256

Pin Configurations

Pin Name	Function
A0 - A1	Address Inputs
SDA	Serial Data
SCL	Serial Clock Input
WP	Write Protect
NC	No Connect
GND	Ground

8-lead PDIP

8-ball dBGA2

Bottom View

1 (8)

A0

GND

8 🗆 VCC 7 🗋 WP

6 🗅 SCL

5 🗅 SDA

A0 🗔	1 8	
A1 🗔	2 7	🗆 WP
NC 🖂	3 6	SCL
GND 🖂	4 5	🔤 SDA

8-lead SOIC

8-lead TSSOP

0	ou	410	00	
		$\overline{\bigcirc}$		1
A0 🗆	1		8	b vcc
A1 🗆	2		7	D WP
NC 🗆	3		6	
GND 🗆	4		5	🗆 SDA
]

8-lead MAP					
VCC WP	8	Ц	A0		
WP	7	2	A1		
SCL	6	3	NC		
SDA	5	4	GND		

Bottom View

Bev. 0670N-SEEPR-4/04





Absolute Maximum Ratings*

Operating Temperature55°C to +125°C
Storage Temperature65°C to +150°C
Voltage on Any Pin with Respect to Ground1.0V to +7.0V
Maximum Operating Voltage 6.25V
DC Output Current 5.0 mA

*NOTICE: Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Block Diagram



Pin Description SERIAL CLOCK (SCL): The SCL input is used to positive edge clock data into each EEPROM device and negative edge clock data out of each device.

SERIAL DATA (SDA): The SDA pin is bidirectional for serial data transfer. This pin is opendrain driven and may be wire-ORed with any number of other open-drain or open collector devices.

DEVICE/ADDRESSES (A1, A0): The A1 and A0 pins are device address inputs that are hardwired or left not connected for hardware compatibility with other AT24CXX devices. When the pins are hardwired, as many as four 128K/256K devices may be addressed on a single bus system (device addressing is discussed in detail under the Device Addressing section). If the pins are left floating, the A1 and A0 pins will be internally pulled down to GND if the capacitive coupling to the circuit board V_{CC} plane is <3 pF. If coupling is >3 pF, Atmel recommends connecting the address pins to GND.

WRITE PROTECT (WP): The write protect input, when connected to GND, allows normal write operations. When WP is connected high to V_{CC} , all write operations to the memory are inhibited. If the pin is left floating, the WP pin will be internally pulled down to GND if the capacitive coupling to the circuit board V_{CC} plane is <3 pF. If coupling is >3 pF, Atmel recommends connecting the pin to GND.

Memory Organization

AT24C128/256, 128K/256K SERIAL EEPROM: The 128K/256K is internally organized as 256/512 pages of 64-bytes each. Random word addressing requires a 14/15-bit data word address.





Pin Capacitance⁽¹⁾

Applicable over recommended operating range from $T_A = 25^{\circ}C$, f = 1.0 MHz, $V_{CC} = +1.8V$.

Symbol	Test Condition	Мах	Units	Conditions
C _{I/O}	Input/Output Capacitance (SDA)	8	pF	$V_{I/O} = 0V$
C _{IN}	Input Capacitance (A ₀ , A ₁ , SCL)	6	pF	$V_{IN} = 0V$

Note: 1. This parameter is characterized and is not 100% tested.

DC Characteristics⁽¹⁾

Applicable over recommended operating range from: $T_{AI} = -40^{\circ}C$ to $+85^{\circ}C$, $V_{CC} = +1.8V$ to +5.5V; $T_{AE} = -40^{\circ}C$ to $+125^{\circ}C^{(2)}$, $V_{CC} = +2.7V$ to +5.5V(unless otherwise noted).

Symbol	Parameter	Test Condition		Min	Тур	Max	Units
V _{CC1}	Supply Voltage			1.8		3.6	V
V _{CC2}	Supply Voltage			2.5		5.5	V
V _{CC3}	Supply Voltage			4.5		5.5	V
I _{CC1}	Supply Current	$V_{\rm CC} = 5.0 V$	READ at 400 kHz		1.0	2.0	mA
I _{CC2}	Supply Current	$V_{CC} = 5.0V$	WRITE at 400 kHz		2.0	3.0	mA
	Standby Current	V _{CC} = 1.8V				0.2	μA
I _{SB1}	(1.8V option)	V _{CC} = 3.6V	$V_{IN} = V_{CC} \text{ or } V_{SS}$			2.0	
	Standby Current	V _{CC} = 2.5V				0.5	μA
I _{SB2}	(2.5V option)	V _{CC} = 5.5V	$V_{IN} = V_{CC} \text{ or } V_{SS}$			6.0	
I _{SB3}	Standby Current (5.0V option)	V _{CC} = 4.5 - 5.5V	$V_{IN} = V_{CC} \text{ or } V_{SS}$			6.0	μA
ILI	Input Leakage Current	$V_{IN} = V_{CC} \text{ or } V_{SS}$			0.10	3.0	μA
I _{LO}	Output Leakage Current	$V_{OUT} = V_{CC} \text{ or } V_{SS}$			0.05	3.0	μA
V _{IL}	Input Low Level ⁽¹⁾			-0.6		V _{CC} x 0.3	V
V _{IH}	Input High Level ⁽¹⁾			V _{CC} x 0.7		V _{CC} + 0.5	V
V _{OL2}	Output Low Level	$V_{CC} = 3.0V$	I _{OL} = 2.1 mA			0.4	V
V _{OL1}	Output Low Level	V _{CC} = 1.8V	I _{OL} = 0.15 mA			0.2	V

Notes: 1. $V_{\rm IL}$ min and $V_{\rm IH}$ max are reference only and are not tested.

2. The AT24C128/256 bearing the process letter "B" on the package (the mark is located in the lower right corner on the topside of the package) are approved for operation in the extended temperature range.

AT24C128/256

AC Characteristics – Industrial Tempuatures

Applicable over recommended operating range from $T_{AI} = -40^{\circ}C$ to $+85^{\circ}C$, $V_{CC} = +1.8V$ to +5.5V, CL = 100 pF (unless otherwise noted). Test conditions are listed in Note 2.

		1.8-volt 2.5		.5-volt	5	5.0-volt		
Symbol	Parameter	Min	Max	Min	Max	Min	Max	Units
f _{SCL}	Clock Frequency, SCL		100		400		1000	kHz
t _{LOW}	Clock Pulse Width Low	4.7		1.3		0.4		μs
t _{HIGH}	Clock Pulse Width High	4.0		0.6		0.4		μs
t _{AA}	Clock Low to Data Out Valid	0.1	4.5	0.05	0.9	0.05	0.55	μs
t _{BUF}	Time the bus must be free before a new transmission can start ⁽¹⁾	4.7		1.3		0.5		μs
t _{HD.STA}	Start Hold Time	4.0		0.6		0.25		μs
t _{SU.STA}	Start Set-up Time	4.7		0.6		0.25		μs
t _{HD.DAT}	Data In Hold Time	0		0		0		μs
t _{SU.DAT}	Data In Set-up Time	200		100		100		ns
t _R	Inputs Rise Time ⁽¹⁾		1.0		0.3		0.3	μs
t _F	Inputs Fall Time ⁽¹⁾		300		300		100	ns
t _{SU.STO}	Stop Set-up Time	4.7		0.6		0.25		μs
t _{DH}	Data Out Hold Time	100		50		50		ns
t _{wR}	Write Cycle Time		20 or 5 ⁽³⁾		10 or 5 ⁽³⁾		10 or 5 ⁽³⁾	ms
Endurance ⁽¹⁾	25°C, Page Mode			100k or	1,000,000 ⁽⁴⁾			Write Cycles

Notes: 1. This parameter is characterized and is not 100% tested.

2. AC measurement conditions:

 $\rm R_L$ (connects to $\rm V_{CC}$): 1.3 k Ω (2.5V, 5V), 10 k Ω (1.8V)

Input pulse voltages: 0.3 V_{CC} to 0.7 V_{CC}

Input rise and fall times: \leq 50 ns

Input and output timing reference voltages: 0.5 $\rm V_{\rm CC}$

- 3. The Write Cycle Time of 5 ms only applies to the AT24C128/256 devices bearing the process letter "B" on the package (the mark is located in the lower right corner on the top side of the package).
- 4. The AT24C128/256 bearing the process letter "B" in the package (the mark is located in the lower right corner on the top side of the package), guarantees 1 million write cycle endurance (1.8 3.6V).





AC Characteristics⁽⁵⁾ – Extended Tempuatures

Applicable over recommended operating range from $T_{AE} = -40^{\circ}C$ to $+125^{\circ}C$, $V_{CC} = +2.7V$ to +5.5V, CL = 100 pF (unless otherwise noted). Test conditions are listed in Note 2.

		2	2.7-volt	5	.0-volt	
Symbol	Parameter	Min	Мах	Min	Мах	Units
f _{SCL}	Clock Frequency, SCL		400		1000	kHz
t _{LOW}	Clock Pulse Width Low	1.3		0.4		μs
t _{HIGH}	Clock Pulse Width High	0.6		0.4		μs
t _{AA}	Clock Low to Data Out Valid	0.05	0.9	0.05	0.55	μs
t _{BUF}	Time the bus must be free before a new transmission can start ⁽¹⁾	1.3		0.5		μs
t _{HD.STA}	Start Hold Time	0.6		0.25		μs
t _{SU.STA}	Start Set-up Time	0.6		0.25		μs
t _{HD.DAT}	Data In Hold Time	0		0		μs
t _{SU.DAT}	Data In Set-up Time	100		100		ns
t _R	Inputs Rise Time ⁽¹⁾		0.3		0.3	μs
t _F	Inputs Fall Time ⁽¹⁾		300		100	ns
t _{SU.STO}	Stop Set-up Time	0.6		0.25		μs
t _{DH}	Data Out Hold Time	50		50		ns
t _{WR}	Write Cycle Time		10 or 5 ⁽³⁾		10 or 5 ⁽³⁾	ms
Endurance ⁽¹⁾	25°C, Page Mode		100k or 1	,000,000 ⁽⁴⁾		Write Cycles

Notes: 1. This parameter is characterized and is not 100% tested.

2. AC measurement conditions:

 $\rm R_L$ (connects to V_{CC}): 1.3 k\Omega (2.5V, 5V), 10 kΩ (1.8V)

Input pulse voltages: 0.3 V_{CC} to 0.7 V_{CC}

Input rise and fall times: \leq 50 ns

Input and output timing reference voltages: 0.5 $\rm V_{\rm CC}$

- 3. The Write Cycle Time of 5 ms only applies to the AT24C128/256 devices bearing the process letter "B" on the package (the mark is located in the lower right corner on the top side of the package).
- 4. The AT24C128/256 bearing the process letter "B" in the package (the mark is located in the lower right corner on the top side of the package), guarantees 1 million write cycle endurance (1.8 3.6V).
- 5. The AT24C128/256 bearing the process letter "B" on the package (the mark is located in the lower right corner on the topside of the package) are approved for operation in the extended temperature range.

Device Operation

CLOCK and DATA TRANSITIONS: The SDA pin is normally pulled high with an external device. Data on the SDA pin may change only during SCL low time periods (refer to Data Validity timing diagram). Data changes during SCL high periods will indicate a start or stop condition as defined below.

START CONDITION: A high-to-low transition of SDA with SCL high is a start condition which must precede any other command (refer to Start and Stop Definition timing diagram).

STOP CONDITION: A low-to-high transition of SDA with SCL high is a stop condition. After a read sequence, the stop command will place the EEPROM in a standby power mode (refer to Start and Stop Definition timing diagram).

ACKNOWLEDGE: All addresses and data words are serially transmitted to and from the EEPROM in 8-bit words. The EEPROM sends a zero during the ninth clock cycle to acknowledge that it has received each word.

STANDBY MODE: The AT24C128/256 features a low power standby mode which is enabled: a) upon power-up and b) after the receipt of the STOP bit and the completion of any internal operations.

MEMORY RESET: After an interruption in protocol, power loss or system reset, any 2-wire part can be reset by following these steps: (a) Clock up to 9 cycles, (b) look for SDA high in each cycle while SCL is high and then (c) create a start condition as SDA is high.





Bus Timing (SCL: Serial Clock, SDA: Serial Data I/O)



Write Cycle Timing (SCL: Serial Clock, SDA: Serial Data I/O)



Note: 1. The write cycle time t_{WR} is the time from a valid stop condition of a write sequence to the end of the internal clear/write cycle.

Data Validity



Start and Stop Definition



Output Acknowledge







Device Addressing	The 128K/256K EEPROM requires an 8-bit device address word following a start condition to enable the chip for a read or write operation (refer to Figure 1). The device address word consists of a mandatory one, zero sequence for the first five most significant bits as shown. This is common to all 2-wire EEPROM devices.
	The 128K/256K uses the two device address bits A1, A0 to allow as many as four devices on the same bus. These bits must compare to their corresponding hardwired input pins. The A1 and A0 pins use an internal proprietary circuit that biases them to a logic low condition if the pins are allowed to float.
	The eighth bit of the device address is the read/write operation select bit. A read operation is initiated if this bit is high and a write operation is initiated if this bit is low.
	Upon a compare of the device address, the EEPROM will output a zero. If a compare is not made, the device will return to a standby state.
	DATA SECURITY: The AT24C128/256 has a hardware data protection scheme that allows the user to write protect the whole memory when the WP pin is at V_{CC} .
Write Operations	BYTE WRITE: A write operation requires two 8-bit data word addresses following the device address word and acknowledgment. Upon receipt of this address, the EEPROM will again respond with a zero and then clock in the first 8-bit data word. Following receipt of the 8-bit data word, the EEPROM will output a zero. The addressing device, such as a microcontroller, then must terminate the write sequence with a stop condition. At this time the EEPROM enters an internally-timed write cycle, t_{WR} , to the nonvolatile memory. All inputs are disabled during this write cycle and the EEPROM will not respond until the write is complete (refer to Figure 2).
	PAGE WRITE: The 128K/256K EEPROM is capable of 64-byte page writes.
	A page write is initiated the same way as a byte write, but the microcontroller does not send a stop condition after the first data word is clocked in. Instead, after the EEPROM acknowledges receipt of the first data word, the microcontroller can transmit up to 63 more data words. The EEPROM will respond with a zero after each data word received. The microcontroller must ter-

minate the page write sequence with a stop condition (refer to Figure 3).

The data word address lower 6 bits are internally incremented following the receipt of each data word. The higher data word address bits are not incremented, retaining the memory page row location. When the word address, internally generated, reaches the page boundary, the following byte is placed at the beginning of the same page. If more than 64 data words are transmitted to the EEPROM, the data word address will "roll over" and previous data will be overwritten. The address "roll over" during write is from the last byte of the current page to the first byte of the same page.

ACKNOWLEDGE POLLING: Once the internally-timed write cycle has started and the EEPROM inputs are disabled, acknowledge polling can be initiated. This involves sending a start condition followed by the device address word. The read/write bit is representative of the operation desired. Only if the internal write cycle has completed will the EEPROM respond with a zero, allowing the read or write sequence to continue.

Read Operations

Read operations are initiated the same way as write operations with the exception that the read/write select bit in the device address word is set to one. There are three read operations: current address read, random address read and sequential read.

CURRENT ADDRESS READ: The internal data word address counter maintains the last address accessed during the last read or write operation, incremented by one. This address stays valid between operations as long as the chip power is maintained. The address "roll over" during read is from the last byte of the last memory page, to the first byte of the first page.

Once the device address with the read/write select bit set to one is clocked in and acknowledged by the EEPROM, the current address data word is serially clocked out. The microcontroller does not respond with an input zero but does generate a following stop condition (refer to Figure 4).

RANDOM READ: A random read requires a "dummy" byte write sequence to load in the data word address. Once the device address word and data word address are clocked in and acknowledged by the EEPROM, the microcontroller must generate another start condition. The microcontroller now initiates a current address read by sending a device address with the read/write select bit high. The EEPROM acknowledges the device address and serially clocks out the data word. The microcontroller does not respond with a zero but does generate a following stop condition (refer to Figure 5).

SEQUENTIAL READ: Sequential reads are initiated by either a current address read or a random address read. After the microcontroller receives a data word, it responds with an acknowledge. As long as the EEPROM receives an acknowledge, it will continue to increment the data word address and serially clock out sequential data words. When the memory address limit is reached, the data word address will "roll over" and the sequential read will continue. The sequential read operation is terminated when the microcontroller does not respond with a zero but does generate a following stop condition (refer to Figure 6).

Figure 1. Device Address











Notes: (* = DON'T CARE bit) († = DON'T CARE bit for the 128K)

Figure 4. Current Address Read



Figure 5. Random Read



(+ = DON'T CARE bit)(+ = DON'T CARE bit for the 128K)





AT24C128 Ordering Information

Ordering Code	Package	Operation Range
AT24C128-10PI-2.7	8P3	
AT24C128N-10SI-2.7	8S1	
AT24C128W-10SI-2.7	8S2	Industrial Temperature
AT24C128U2-10UI-2.7	8U2-1	(-40°C to 85°C)
AT24C128Y1-10YI-2.7	8Y1	
AT24C128-10TI-2.7	8A2	
AT24C128-10PI-1.8	8P3	
AT24C128N-10SI-1.8	8S1	
AT24C128W-10SI-1.8	8S2	Industrial Temperature
AT24C128U2-10UI-1.8	8U2-1	(-40°C to 85°C)
AT24C128Y1-10YI-1.8	8Y1	
AT24C128-10TI-1.8	8A2	
AT24C128N-10SE-2.7	8S1	High Grade/ Extended Temperature (-40°C to 125°C)
AT24C128N-10SU-2.7	8S1	
AT24C128N-10SU-1.8	8S1	Lead-free/Halogen-free/ Industrial Temperature
AT24C128-10TU-2.7	8A2	
AT24C128-10TU-1.8	8A2	(-40°C to 85°C)

Note: For 2.7V devices used in the 4.5V to 5.5V range, please refer to performance values in the AC and DC characteristics tables.

	Package Type				
8P3	8-lead, 0.300" Wide, Plastic Dual Inline Package (PDIP)				
8S1	8-lead, 0.150" Wide, Plastic Gull Wing Small Outline Package (JEDEC SOIC)				
8S2	8-lead, 0.200" Wide, Plastic Gull Wing Small Outline Package (EIAJ SOIC)				
8U2-1	8-ball, die Ball Grid Array Package (dBGA2)				
8Y1	8-lead, 4.90 mm x 3.00 mm Body, Dual Footprint, Non-leaded, Miniature Array Package (MAP)				
8A2	8-lead, 0.170" Wide, Thin Shrink Small Outline Package (TSSOP)				
Options					
-2.7	Low-voltage (2.7V to 5.5V)				
-1.8	Low-voltage (1.8V to 3.6V)				





AT24C256 Ordering Information

Ordering Code	Package	Operation Range
AT24C256-10PI-2.7	8P3	
AT24C256N-10SI-2.7	8S1	Inductrial Tomporatura
AT24C256W-10SI-2.7	8S2	Industrial Temperature
AT24C256U2-10UI-2.7	8U2-1	(-40°C to 85°C)
AT24C256-10TI-2.7	8A2	
AT24C256-10PI-1.8	8P3	
AT24C256N-10SI-1.8	8S1	Inductrial Tomporature
AT24C256W-10SI-1.8	8S2	Industrial Temperature
AT24C256U2-10UI-1.8	8U2-1	(-40°C to 85°C)
AT24C256-10TI-1.8	8A2	
AT24C256N-10SE-2.7	8S1	High Grade/ Extended Temperature (-40°C to 125°C)
AT24C256N-10SU-2.7	8S1	
AT24C256N-10SU-1.8	8S1	Lead-free/Halogen-free/
AT24C256-10TU-2.7	8A2	Industrial Temperature
AT24C256-10TU-1.8	8A2	(-40°C to 85°C)

Note: For 2.7V devices used in the 4.5V to 5.5V range, please refer to performance values in the AC and DC characteristics tables.

Package Type		
8P3	8-lead, 0.300" Wide, Plastic Dual Inline Package (PDIP)	
8S1	8-lead, 0.150" Wide, Plastic Gull Wing Small Outline Package (JEDEC SOIC)	
8S2	8-lead, 0.200" Wide, Plastic Gull Wing Small Outline Package (EIAJ SOIC)	
8U2-1	8-ball, die Ball Grid Array Package (dBGA2)	
8A2	8-lead, 0.170" Wide, Thin Shrink Small Outline Package (TSSOP)	
Options		
-2.7	Low-voltage (2.7V to 5.5V)	
-1.8	Low-voltage (1.8V to 3.6V)	

14 AT24C128/256

AT24C128/256

Packaging Information

8P3 – PDIP







8S1 – JEDEC SOIC



AT24C128/256

8S2 – EIAJ SOIC







8U2-1 – dBGA2









8A2 – TSSOP





Atmel Corporation

2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311 Fax: 1(408) 487-2600

Regional Headquarters

Europe

Atmel Sarl Route des Arsenaux 41 Case Postale 80 CH-1705 Fribourg Switzerland Tel: (41) 26-426-5555 Fax: (41) 26-426-5500

Asia

Room 1219 Chinachem Golden Plaza 77 Mody Road Tsimshatsui East Kowloon Hong Kong Tel: (852) 2721-9778 Fax: (852) 2722-1369

Japan

9F, Tonetsu Shinkawa Bldg. 1-24-8 Shinkawa Chuo-ku, Tokyo 104-0033 Japan Tel: (81) 3-3523-3551 Fax: (81) 3-3523-7581

Atmel Operations

Memory 2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311 Fax: 1(408) 436-4314

Microcontrollers

2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311 Fax: 1(408) 436-4314

La Chantrerie BP 70602 44306 Nantes Cedex 3, France Tel: (33) 2-40-18-18-18 Fax: (33) 2-40-18-19-60

ASIC/ASSP/Smart Cards

Zone Industrielle 13106 Rousset Cedex, France Tel: (33) 4-42-53-60-00 Fax: (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906, USA Tel: 1(719) 576-3300 Fax: 1(719) 540-1759

Scottish Enterprise Technology Park Maxwell Building East Kilbride G75 0QR, Scotland Tel: (44) 1355-803-000 Fax: (44) 1355-242-743 **RF**/Automotive

Theresienstrasse 2 Postfach 3535 74025 Heilbronn, Germany Tel: (49) 71-31-67-0 Fax: (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906, USA Tel: 1(719) 576-3300 Fax: 1(719) 540-1759

Biometrics/Imaging/Hi-Rel MPU/ High Speed Converters/RF Datacom Avenue de Rochepleine BP 123 38521 Saint-Egreve Cedex, France Tel: (33) 4-76-58-30-00 Fax: (33) 4-76-58-34-80

Literature Requests www.atmel.com/literature

Disclaimer: Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

© Atmel Corporation 2004. All rights reserved. Atmel[®] and combinations thereof, are the registered trademarks, and dBGA2[™] is the trademark of Atmel Corporation or its subsidiaries. Other terms and product names may be the trademarks of others.

