



COMPLIANT

Precision 8-Ch/Dual 4-Ch Low Voltage Analog Multiplexers

DESCRIPTION

The DG3408, DG3409 uses BiCMOS wafer fabrication technology that allows the DG3408/3409 to operate on single and dual supplies. Single supply voltage ranges from 3 V to 12 V while dual supply operation is recommended with \pm 3 V to \pm 6 V.

The DG3408 is an 8-channel single-ended analog multiplexer designed to connect one of eight inputs to a common output as determined by a 3-bit binary address (A_0, A_1, A_2) . The DG3409 is a dual 4-channel differential analog multiplexer designed to connect one of four differential inputs to a common dual output as determined by its 2-bit binary address (A_0, A_1) . Break-before-make switching action to protect against momentary crosstalk between adjacent channels.

FEATURES

- 2.7 V to 12 V single supply or ± 3 to ± 6 V dual supply operation
- Low on-resistance R_{ON}: 3.9 Ω typ.
- Fast switching: t_{ON} 42 ns, t_{OFF} 24 ns
- · Break-before-make guaranteed
- Low leakage
- TTL, CMOS, LV logic (3 V) compatible
- 2000 V ESD protection (HBM)
- MICRO FOOT[®] package
- · Lead (Pb)-free solder bumps
- Compliant to RoHS Directive 2002/95/EC


BENEFITS


- · High accuracy
- Single and dual power rail capacity
- · Wide operating voltage range
- Simple logic interface

APPLICATIONS

- · Data acquisition systems
- Battery operated equipment
- · Portable test equipment
- Sample and hold circuits
- Communication systems
- SDSL, DSLAM
- · Audio and video signal routing

FUNCTIONAL BLOCK DIAGRAM AND PIN CONFIGURATION





Document Number: 72858 S11-0303-Rev. E, 28-Feb-11

Vishay Siliconix



| TRUTH TABLE (DG3408) | | | | | | | |
|----------------------|----------------|----------------|----|-----------|--|--|--|
| A ₂ | A ₁ | A ₀ | EN | On Switch | | | |
| Х | Х | Х | 1 | None | | | |
| 0 | 0 | 0 | 0 | 1 | | | |
| 0 | 0 | 1 | 0 | 2 | | | |
| 0 | 1 | 0 | 0 | 3 | | | |
| 0 | 1 | 1 | 0 | 4 | | | |
| 1 | 0 | 0 | 0 | 5 | | | |
| 1 | 0 | 1 | 0 | 6 | | | |
| 1 | 1 | 0 | 0 | 7 | | | |
| 1 | 1 | 1 | 0 | 8 | | | |

| TRUTH TABLE (DG3409) | | | | | | | |
|----------------------|-------|----|-----------|--|--|--|--|
| A ₁ | A_0 | EN | On Switch | | | | |
| Х | Х | 1 | None | | | | |
| 0 | 0 | 0 | 1 | | | | |
| 0 | 1 | 0 | 2 | | | | |
| 1 | 0 | 0 | 3 | | | | |
| 1 | 1 | 0 | 4 | | | | |

X = Do not care

For low and high voltage levels for V_{AX} and V_{EN} consult "Digital Control" Parameters for Specific V+ operation. See Specifications Tables for:

Single Supply 12 V

Dual Supply V+ = 5 V, V- = -5 V

Single Supply 5 V

Single Supply 3 V

| ORDERING INFORMATION (DG3408) | | | | | |
|-------------------------------|---|------------------------------------|--|--|--|
| Temperature Range | Package | Part Number | | | |
| - 40 °C to 85 °C | MICRO FOOT: 16-Bump (4 x 4, 0.5 mm Pitch, 238 µm Bump Height) | DG3408DB-T2-E1 (Lead (Pb)-free) | | | |

| ORDERING INFORMATION (DG3409) | | | | | |
|--------------------------------------|---|------------------------------------|--|--|--|
| Temperature Range | Package | Part Number | | | |
| - 40 °C to 85 °C | MICRO FOOT: 16-Bump (4 x 4, 0.5 mm Pitch, 238 μm Bump Height) | DG3409DB-T2-E1 (Lead (Pb)-free) | | | |

| ABSOLUTE MAXIMUM RATING | $15 (1_A = 25 ^{\circ}\text{C}, \text{ unless otherwise not})$ | ea) | | | |
|---|---|-----------------------------|----|--|--|
| Parameter | Limit | Unit | | | |
| Voltage Referenced V+ to V- | | 14 | | | |
| GND | | 7 | V | | |
| Digital Inputs ^a , V _S , V _D | | (V-) - 0.3 V to (V) + 0.3 V | | | |
| Current (Any Terminal Except S or D) | | 30 | | | |
| Continuous Current, S or D) | | | | | |
| Peak Current, S or D (Pulsed at 1 ms, 10 % du | ty cycle max). | 200 | | | |
| Package Solder Reflow Conditions ^b | IR/Convection | 250 | °C | | |
| Storage Temperature | | - 65 to 150 | | | |
| Power Dissipation (Package) ^c , (T _A = 70 °C) | 16-Bump (4 x 4 mm) MICRO FOOT ^d | 719 | mW | | |

Notes:

- a. Signals on S_X , D_X or IN_X exceeding V+ or V- will be clamped by internal diodes. Limit forward diode current to maximum current ratings.
- b. Refer to IPC/JEDEC (J-STD-020).
- c. All bumps soldered or welded to PC board.
- d. Derate 9 mW/°C above 70 °C.





| | | Test Conditions Unless Otherwise Specifi V+ = 12 V, ± 10 %, V- = 0 | | | - 4 | Limits 0 °C to 85 | °C | |
|---|-----------------------------|---|--|--------------|-------------|----------------------|----------|------|
| Parameter | Symbol | V_A , $V_{\overline{EN}} = 0.8 \text{ V or } 2.4 \text{ V}$ | _ | Temp.b | Min.c | Typ. ^d | Max.c | Unit |
| Analog Switch | | | | - | | | | |
| Analog Signal Range ^e | V _{ANALOG} | | | Full | 0 | | 12 | V |
| On-Resistance | R _{ON} | $V+ = 10.8 \text{ V}, V_D = 2 \text{ V or } 9 \text{ V}, I_S = 0$ Sequence Each Switch O | | Room Full | | 4 | 7 7.5 | |
| R _{ON} Match Between Channels ^g | ΔR_{ON} | | | Room | | | 3.6 | Ω |
| On-Resistance Flatness ⁱ | R _{ON} Flatness | V+ = 10.8 V, V _D = 2 V or 9 V, I _S : | = 50 mA | Room | | | 8 | |
| Switch Off Leakage Current | I _{S(off)} | V _{EN} = 2.4 V, V _D = 11 V or 1 V, V _S = | 1 V or 11 V | Room Full | - 2 - 20 | | 2 20 | |
| ownor on Educago durioni | I _{D(off)} | VEN = 2.1. V, VD = 11 V 51 1 V, VS = | | Room Full | - 2 - 20 | | 2 20 | nA |
| Channel On Leakage Current | $I_{D(on)}$ | $V_{\overline{EN}} = 0 \text{ V}, V_{S} = V_{D} = 1 \text{ V or } 11 \text{ V}$ | | Room Full | - 2 - 20 | | 2 20 | |
| Digital Control | | | | | | | | |
| Logic High Input Voltage | V _{INH} | | | Full | 2.4 | | | V |
| Logic Low Input Voltage | V_{INL} | | | Full | | | 8.0 | · |
| Input Current | I _{IN} | $V_{AX} = V_{\overline{EN}} = 2.4 \text{ V or } 0.8$ | V | Full | - 1 | | 1 | μΑ |
| Dynamic Characteristics | | | | | | | | |
| Transition Time | t _{TRANS} | | $V_{S1} = 8 \text{ V, } V_{S8} = 0 \text{ V, } (DG3408)$ $V_{S1b} = 8 \text{ V, } V_{S4b} = 0 \text{ V, } (DG3409)$ see figure 2 | | | 42 | 71 75 | |
| Break-Before-Make Time | t _{BBM} | $V_{S(all)} = V_{DA} = 5 V$ see figure 4 | | Room Full | 2 | 24 | | ns |
| Enable Turn-On Time | t _{ON(ĒN)} | V _{AX} = 0 V, V _{S1} = 5 V (DG34 V _{AX} = 0 V, V _{S1b} = 5 V (DG34 | | Room Full | | 42 | 70 75 | |
| Enable Turn-Off Time | $t_{OFF(\overline{EN})}$ | see figure 3 | | Room Full | | 24 | 44 46 | |
| Charge Injection ^e | Q | $C_L = 1 \text{ nF, } V_{GEN} = 0 \text{ V, } R_{GEN}$ | = 0 Ω | Room | | 29 | | рC |
| Off Isolation ^{e, h} | OIRR | $f = 100 \text{ kHz}, R_L = 1 \text{ k}\Omega$ | | Room | | - 80 | | dB |
| Crosstalk ^e | X _{TALK} | 1 - 100 M12, 11 <u>L</u> - 1 M22 | | Room | | - 85 | | ub |
| Source Off Capacitance ^e | C _{S(off)} | $f = 1 \text{ MHz}, V_S = 0 \text{ V}, V_{\overline{EN}} = 2.4 \text{ V}$ | DG3408 DG3409 | Room Room | | 21 23 | | |
| Drain Off Capacitance ^e | C _{D(off)} | $f = 1 \text{ MHz}, V_D = 0 \text{ V}, V_{\overline{EN}} = 2.4 \text{ V}$ | DG3408 DG3409 | Room | | 211 112 | | pF |
| Drain On Capacitance ^e | C _{D(on)} | f = 1 MHz, V _D = 0 V, V _{EN} = 0 V | DG3408 | Room | | 238 | | |
| Power Supplies | | | 20700 | 1100111 | | 1.57 | <u> </u> | |
| Power Supply Current | l+ | $V_{\overline{EN}} = V_A = 0 \text{ V or V} +$ | | Room | | | 1 | μΑ |

Vishay Siliconix



| | | Test Conditions Unless Otherwise Specified V+ = 5 V, V- = - 5 V, ± 10 % | | | - 40 | Limits °C to 85 | °C | |
|---|-----------------------------|--|------------------|--------------|-------------|--------------------|----------|----|
| Parameter | Symbol | V_A , $V_{\overline{EN}} = 0.8 \text{ V or } 2 \text{ V}^f$ | | Temp.b | Min.c | Typ. ^d | Max.c | Un |
| Analog Switch | | | | | | | | |
| Analog Signal Range ^e | V _{ANALOG} | | | Full | - 5 | | 5 | \ |
| On-Resistance | R _{ON} | V+ = 4.5 V, V- = - 4.5 V, V_D = \pm 3.5 V, I_S = sequence each switch on | = 50 mA, | Room Full | | 5 | 8 8.5 | |
| R _{ON} Match Between Channels ^g | ΔR_{ON} | | | Room | | | 3.6 | (|
| On-Resistance Flatness ⁱ | R _{ON} Flatness | $V+ = 4.5 \text{ V}, V- = -4.5 \text{ V}, V_D = \pm 3.5 \text{ V}, I_S$ | = 50 mA | Room | | | 8.2 | |
| Switch Off Leakage Current ^a | I _{S(off)} | V+ = 5.5, V- = - 5.5 V | | Room Full | - 2 - 20 | | 2 20 | |
| Switch Oil Leakage Current | I _{D(off)} | $V_{\overline{EN}} = 2.4 \text{ V}, V_D = \pm 4.5 \text{ V}, V_S = \pm 4$ | I.5 V | Room Full | - 2 - 20 | | 2 20 | n |
| Channel On Leakage Current ^a | $I_{D(on)}$ | V+ = 5.5 V, V- = -5.5 V $V_{\overline{EN}} = 0 \text{ V}, V_D = \pm 4.5 \text{ V}, V_S = \pm 4.5 \text{ V}$ | 5 V | Room Full | - 2 - 20 | | 2 20 | |
| Digital Control | | | | | | | | |
| Logic High Input Voltage | V_{INH} | | | | 2 | | | , |
| Logic Low Input Voltage | V_{INL} | | | Full | | | 0.8 | |
| Input Current ^a | I_{IN} | $V_{AX} = V_{EN} = 2 \text{ V or } 0.8 \text{ V}$ | | Full | - 1 | | 1 | Ļ |
| Dynamic Characteristics | | | | | | | | |
| Transition Time ^e | t _{TRANS} | $V_{S1} = 3.5 \text{ V}, V_{S8} = -3.5 \text{ V}, (DG340)$ $V_{S1b} = 3.5 \text{ V}, V_{S4b} = -3.5 \text{ V}, (DG340)$ see figure 2 | | Room Full | | 68 | 89 94 | |
| Break-Before-Make Time ^e | t _{BBM} | V _{S(all)} = V _{DA} = 3.5 V see figure 4 | | Room Full | 1 | 16 | | r |
| Enable Turn-On Time ^e | t _{ON(ĒN)} | V _{AX} = 0 V, V _{S1} = 3.5 V (DG3408 V _{AX} = 0 V, V _{S1b} = 3.5 V (DG3408 | | Room Full | | 68 | 88 94 | |
| Enable Turn-Off Time ^e | $t_{OFF(\overline{EN})}$ | $v_{AX} = 0$ V, $v_{S1b} = 3.5$ V (DG340) see figure 3 | J) | Room Full | | 58 | 78 81 | |
| Source Off Capacitance ^e | $C_{S(off)}$ | $f = 1 \text{ MHz}$. $V_c = 0 \text{ V}$. $V_{\overline{EN}} = 2 \text{ V}$ | DG3408 DG3409 | Room Room | | 23 23 | | |
| Drain Off Capacitance ^e | C _{D(off)} | $t = 1 \text{ MHz}$. $V_D = 0 \text{ V}$. $V_{\overline{EN}} = 2 \text{ V}$ | DG3408 DG3409 | Room Room | | 223 113 | | þ |
| Drain On Capacitance ^e | C _{D(on)} | f = 1 MHz, V _D = 0 V, V _{EN} = 0 V DG3408 DG3409 | | Room | | 246 137 | | |
| Power Supplies | | | | | | | | |
| Power Supply Current | l+ | $V_{\overline{FN}} = V_A = 0 \text{ V or V} +$ | | Room | | | 1 | μ |



Vishay Siliconix

| | | Test Conditions Unless Otherwise Specifi V+ = 5 V, ± 10 %, V- = 0 V | | | - 40 | Limits 0 °C to 85 | °C | |
|---|-----------------------------|--|----------------------------|--------------|-------------|-------------------|------------|------|
| Parameter | Symbol | $V_{A}, V_{\overline{EN}} = 0.8 \text{ V or } 2 \text{ V}^{f}$ | | Temp.b | Min.c | Typ.d | Max.c | Unit |
| Analog Switch | | | | | | | | |
| Analog Signal Range ^e | V _{ANALOG} | | | Full | 0 | | 5 | ٧ |
| On-Resistance | R _{ON} | $V+ = 4.5 \text{ V}, V_D \text{ or } V_S = 1 \text{ V or } 3.5 \text{ V},$ | I _S = 50 mA | Room Full | | 7 | 10.5 11 | |
| R _{ON} Match Between Channels ^g | ΔR_{ON} | | | Room | | | 3.6 | Ω |
| On-Resistance Flatness ⁱ | R _{ON} Flatness | $V+ = 4.5 \text{ V}, V_D = 1 \text{ V or } 3.5 \text{ V}, I_S = 1 \text{ V}$ | = 50 mA | Room | | | 9 | |
| Switch Off Leakage Current ^a | I _{S(off)} | V+ = 5.5 V | | Room Full | - 2 - 20 | | 2 20 | |
| Switch Oil Leakage Current | I _{D(off)} | $V_S = 1 \text{ V or } 4 \text{ V}, V_D = 4 \text{ V or}$ | 1 V | Room Full | - 2 - 20 | | 2 20 | nA |
| Channel On Leakage Current ^a | I _{D(on)} | $V_{D} = V_{S} = 1 V \text{ or } 4 V, \text{ sequence eac}$ | h switch on | Room Full | - 2 - 20 | | 2 20 | |
| Digital Control | | , | | T | | ı | | ı |
| Logic High Input Voltage | V _{INH} | V+ = 5 V | | Full | 2 | | | V |
| Logic Low Input Voltage | V _{INL} | | | Full | | | 0.8 | |
| Input Current ^a | I _{IN} | $V_{AX} = V_{\overline{EN}} = 2 \text{ V or } 0.8 \text{ V}$ | | Full | - 1 | | 1 | μΑ |
| Dynamic Characteristics | | | | ı | | Т | | ı |
| Transition Time ^e | t _{TRANS} | $V_{S1} = 3.5 \text{ V}, V_{S8} = 0 \text{ V}, (DG3408)$ $V_{S1b} = 3.5 \text{ V}, V_{S4b} = 0 \text{ V}, (DG3409)$ see figure 2 | | Room Full | | 73 | 94 104 | |
| Break-Before-Make Time ^e | t _{OPEN} | $V_{S(all)} = V_{DA} = 3.5 \text{ V}$ see figure 4 | | Room Full | 2 | 29 | | ns |
| Enable Turn-On Time ^e | t _{ON(ĒN)} | V _{AX} = 0 V, V _{S1} = 3.5 V (DG3- V _{AX} = 0 V, V _{S1b} = 3.5 V (DG3- | | Room Full | | 74 | 94 104 | |
| Enable Turn-Off Time ^e | t _{OFF(EN)} | see figure 3 | | Room Full | | 38 | 57 61 | |
| Charge Injection ^e | Q | $C_L = 1 \text{ nF, } R_{GEN} = 0 \Omega, V_{GEN} = 0$ | = 0 V | Room | | 20 | | рC |
| Off Isolation ^{e, h} | OIRR | $R_L = 1 \text{ k}\Omega, f = 100 \text{ kHz}$ | | Room | | - 81 | | dB |
| Crosstalk ^e | X _{TALK} | 11L - 1 1/22, 1 - 100 KHZ | | Room | | - 85 | | uБ |
| Source Off Capacitance ^e | C _{S(off)} | f = 1 MHz, V _S = 0 V, V _{FN} = 0 V | DG3408 | Room | _ | 22 | | |
| Course on Capacitation | J(011) | LIN | DG3409 | Room | | 24 | | |
| Drain Off Capacitance ^e | $C_{D(off)}$ | $f = 1 \text{ MHz}, V_D = 0 \text{ V}, V_{\overline{EN}} = 2 \text{ V}$ | DG3408 DG3409 | Room | | 223 113 | | pF |
| Drain On Capacitance ^e | C _{D(on)} | $f = 1 \text{ MHz}, V_D = 0 \text{ V}, V_{\overline{EN}} = 0 \text{ V}$ | DG3409 DG3408 DG3409 | Room | | 244 143 | | |
| Power Supplies | | | DG3409 | 1100111 | | 1+3 | | |
| Power Supply Current | I+ | $V_{\overline{EN}} = V_A = 0 \text{ V or V} +$ | | Room | | | 1 | μΑ |

Vishay Siliconix



| | | Test Conditions | - d | | 4.0 | Limits | | |
|--|-----------------------------|---|------------------|--------------|-------------|------------|--------------|------|
| | | Unless Otherwise Specifi V+ = 3 V , $\pm 10 \%$, V- = 0 V | | | - 40 | 0 °C to 85 | , °C | ł |
| Parameter | Symbol | $V_{EN} = 0.4 \text{ V or } 1.8 \text{ V}^{f}$ | | Temp.b | Min.c | Typ.d | Max.c | Unit |
| Analog Switch | | | | | | | | |
| Analog Signal Range ^e | V _{ANALOG} | | | Full | 0 | | 3 | V |
| On-Resistance | R_{ON} | $V+ = 2.7 \text{ V}, V_D = 0.5 \text{ or } 2.2 \text{ V}, I_S$ | = 5 mA | Room Full | | 12 | 25.5 26.5 | |
| R _{ON} Match Between Channels ^g | ΔR _{ON} | V+ = ± 2.7 V, V _D = 0.5 V or 2.2 V, | le = 5 mA | Room | | | 3.6 | Ω |
| On-Resistance Flatness ⁱ | R _{ON} Flatness | = = , 56 5 = , | 5 0 | Room | | | 13 | |
| Switch Off Leakage Current ^a | I _{S(off)} | V+ = 3.3 V | ., | Room Full | - 2 - 20 | | 2 20 | |
| Switch Off Leakage Current | I _{D(off)} | $V_S = 2 \text{ or } 1 \text{ V}, V_D = 1 \text{ or } 2$ | V | Room Full | - 2 - 20 | | 2 20 | nA |
| Channel On Leakage Current ^a | $I_{D(on)}$ | $V_{+} = 3.3 \text{ V}$ $V_{D} = V_{S} = 1 \text{ or } 2 \text{ V}, \text{ sequence each switch on}$ | | Room Full | - 2 - 20 | | 2 20 | |
| Digital Control | | | | | | | | |
| Logic High Input Voltage | V_{INH} | | | Full | 1.8 | | | V |
| Logic Low Input Voltage | V_{INL} | | | Full | | | 0.4 | |
| Input Current ^a | I _{IN} | $V_{AX} = V_{\overline{EN}} = 1.8 \text{ V or } 0.4 \text{ V}$ | | Full | - 1 | | 1 | μΑ |
| Dynamic Characteristics | | | | | | | | |
| Transition Time | t _{TRANS} | $V_{S1} = 1.5 \text{ V}, V_{S8} = 0 \text{ V}, \text{ (DG3-V}_{S1b} = 1.5 \text{ V}, V_{S4b} = 0 \text{ V}, \text{ (DG3-see figure 2})$ | 408) 3409) | Room Full | | 140 | 165 182 | |
| Break-Before-Make Time | t _{BBM} | $V_{S(all)} = V_{DA} = 1.5 \text{ V}$ see figure 4 | | Room Full | 2 | 63 | | ns |
| Enable Turn-On Time | $t_{ON(\overline{EN})}$ | V _{AX} = 0 V, V _{S1} = 1.5 V (DG3- V _{AX} = 0 V, V _{S1b} = 1.5 V (DG3- | 408) 409) | Room Full | | 140 | 162 178 | |
| Enable Turn-Off Time | $t_{OFF(\overline{EN})}$ | see figure 3 | | Room Full | | 76 | 97 104 | |
| Charge Injection ^e | Q | $C_L = 1 \text{ nF, } R_{GEN} = 0, V_{GEN} =$ | 0 V | Room | | 7 | | рC |
| Off Isolation ^{e, h} | OIRR | $f = 100 \text{ kHz}, R_1 = 1 \text{ k}\Omega$ | | Room | | - 81 | | dB |
| Crosstalk ^e | X _{TALK} | 22.2, 1 | T | Room | | - 85 | | |
| Source Off Capacitance ^e | C _{S(off)} | $f = 1 \text{ MHz}, V_S = 0 \text{ V}, V_{\overline{EN}} = 1.8 \text{ V}$ | DG3408 | Room | | 23 | | |
| TIME OF CAPACITATION | 0(011) | | DG3409 | Room | | 25 | | |
| Drain Off Capacitance ^e | C _{D(off)} | $f = 1 \text{ MHz}, V_D = 0 \text{ V}, V_{\overline{EN}} = 1.8 \text{ V}$ | DG3408 | Room | | 230 | | рF |
| , | V- / | | DG3409 | Room | | 120 | | |
| Drain On Capacitance ^e | $C_{D(on)}$ | $f = 1 \text{ MHz}, V_D = 0 \text{ V}, V_{\overline{EN}} = 0 \text{ V}$ | DG3408 DG3409 | Room Room | | 256 147 | | |
| Power Supplies | | | 1 | | | 1 | | |
| Power Supply Current | l+ | $V_{\overline{EN}} = V_A = 0 \text{ V or V} +$ | | Room | | | 1 | μΑ |


Notes:

- a. Leakage parameters are guaranteed by worst case test condition and not subject to production test.
- b. Room = 25 °C, Full = as determined by the operating temperature suffix.
- c. The algebraic convention whereby the most negative value is a minimum and the most positive a maximum, is used in this data sheet.
- d. Typical values are for DESIGN AID ONLY, not guaranteed nor subject to production testing.
- e. Guaranteed by design, not subject to production test.
- f. V_{IN} = input voltage to perform proper function.
- g. $\Delta R_{DON} = R_{DON} Max R_{DON} Min$.
- h. Worst case isolation occurs on Channel 4 due to proximity to the drain pin.
- i. R_{DON} flatness is measured as the difference between the minimum and maximum measured values across a defined Analog signal.


Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.




TYPICAL CHARACTERISTICS (25 °C, unless otherwise noted)




 $\rm R_{ON}$ vs. $\rm V_{COM}$ and Single Supply Voltage




R_{ON} vs. Analog Voltage and Temperature




Leakage Current vs. Analog Voltage



R_{ON} vs. Analog Voltage and Temperature




Supply Current vs. Temperature




Leakage Current vs. Analog Voltage

Vishay Siliconix


TYPICAL CHARACTERISTICS (25 °C, unless otherwise noted)




Switching Time vs. Temperature and Single Supply Voltage




Leakage Current vs. Temperature




Insertion Loss, Off Isolation and Crosstalk vs. Frequency (DG3408)



Transition Time vs. Temperature and Single Supply Voltage




Switching Threshold vs. Supply Voltage



Insertion Loss, Off Isolation and Crosstalk vs. Frequency (DG3409)



TYPICAL CHARACTERISTICS (25 °C, unless otherwise noted)



Supply Current vs. Input Switching Frequency

SCHEMATIC DIAGRAM (Typical Channel)




Figure 1.

Vishay Siliconix

TEST CIRCUITS






Figure 2. Transition Time







Figure 3. Enable Switching Time





TEST CIRCUITS





Return to Specifications: Single Supply 12 V Dual Supply V+ = 5 V, V- = -5 VSingle Supply 5 V Single Supply 3 V

Figure 4. Break-Before-Make Interval




Figure 5. Charge Injection




Figure 6. Off Isolation

TEST CIRCUITS






Figure 7. Crosstalk




Figure 8. Insertion Loss





Figure 9. Source Drain Capacitance



PACKAGE OUTLINE

MICRO FOOT: 16-BUMP (4 x 4, 0.5 mm PITCH, 0.238 mm BUMP HEIGHT)



Notes (Unless Otherwise Specified):

- a. Bump is Lead Free Sn/Ag/Cu.
- b. Non-solder mask defined copper landing pad.
- c. Laser Mark on silicon die back; back-lapped, no coating. Shown is not actual marking; sample only.

| | Millimeters ^a | | Incl | hes |
|----------------|--------------------------|-------|--------|--------|
| Dim. | Min. | Max. | Min. | Max. |
| Α | 0.688 | 0.753 | 0.0271 | 0.0296 |
| A ₁ | 0.218 | 0.258 | 0.0086 | 0.0102 |
| A ₂ | 0.470 | 0.495 | 0.0185 | 0.0195 |
| b | 0.306 | 0.346 | 0.0120 | 0.0136 |
| D | 1.980 | 2.020 | 0.0780 | 0.0795 |
| E | 1.980 | 2.020 | 0.0780 | 0.0795 |
| е | 0.5 BASIC | | 0.0197 | BASIC |
| S | 0.230 | 0.270 | 0.0091 | 0.0106 |


a. Use millimeters as the primary measurement.

Vishay Siliconix maintains worldwide manufacturing capability. Products may be manufactured at one of several qualified locations. Reliability data for Silicon Technology and Package Reliability represent a composite of all qualified locations. For related documents such as package/tape drawings, part marking, and reliability data, see www.vishay.com/ppg?72858.

Document Number: 72858 S11-0303-Rev. E, 28-Feb-11



MICRO FOOT: 16-BUMP (4 mm x 4 mm, 0.5 mm PITCH, 0.238 mm BUMP HEIGHT)



Notes

(unless otherwise specified)

- a. Bump is lead (Pb)-free Sn/Ag/Cu.
- b. Non-solder mask defined copper landing pad.
- c. Laser mark on silicon die back; back-lapped, no coating. Shown is not actual marking; sample only.

| DIM. | MILLIM | ETERS ^a | INCHES | | |
|----------------|--------|--------------------|--------|--------|--|
| DIWI. | MIN. | MAX. | MIN. | MAX. | |
| A | 0.688 | 0.753 | 0.0271 | 0.0296 | |
| A ₁ | 0.218 | 0.258 | 0.0086 | 0.0102 | |
| A ₂ | 0.470 | 0.495 | 0.0185 | 0.0195 | |
| b | 0.306 | 0.346 | 0.0120 | 0.0136 | |
| D | 1.980 | 2.020 | 0.0780 | 0.0795 | |
| E | 1.980 | 2.020 | 0.0780 | 0.0795 | |
| е | 0.5 E | 0.5 BASIC | | BASIC | |
| S | 0.230 | 0.270 | 0.0091 | 0.0106 | |

a. Use millimeters as the primary measurement.

ECN: S11-1065-Rev. A, 13-Jun-11 DWG: 6000

Document Number: 63273

Revision: 13-Jun-11



Legal Disclaimer Notice

Vishay

Disclaimer

ALL PRODUCT, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.

Vishay makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product. To the maximum extent permitted by applicable law, Vishay disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.

Statements regarding the suitability of products for certain types of applications are based on Vishay's knowledge of typical requirements that are often placed on Vishay products in generic applications. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary over time. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts. Product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein.

Except as expressly indicated in writing, Vishay products are not designed for use in medical, life-saving, or life-sustaining applications or for any other application in which the failure of the Vishay product could result in personal injury or death. Customers using or selling Vishay products not expressly indicated for use in such applications do so at their own risk. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay. Product names and markings noted herein may be trademarks of their respective owners.